

WHAT IS CLAIMED IS:

- 1 1. A method of determining a noise-corrected power delay profile, the method
2 comprising:
3 determining a power delay profile;
4 calculating a noise-corrected power delay profile; and
5 wherein the step of calculating the noise-corrected power delay profile comprises
6 using a biased noise-floor power estimate, the power delay profile, and a noise-scaling factor.

- 1 2. The method of claim 1, further comprising:
2 calculating a center-of-gravity position estimate; and
3 wherein the step of calculating the center-of-gravity position estimate comprises using
4 the noise-corrected power delay profile.

- 1 3. The method of claim 1, wherein the noise-scaling factor is applied to the
2 noise-floor power estimate.

- 1 4. The method of claim 1, wherein the noise-scaling factor is dependent upon a
2 probability density function.

1 5. The method of claim 1, wherein:
2 the step of determining the power delay profile comprises using a first plurality of
3 values; and
4 the step of calculating the noise-corrected power delay profile comprises using the
5 first plurality of values and a second plurality of values.

1 6. The method of claim 5, wherein:
2 the first plurality of values is a plurality of power-delay-profile values N_p ; and
3 the second plurality of values is the N_n smallest power-delay-profile values.

1 7. The method of claim 6, wherein the noise-scaling factor is dependent upon a
2 probability density function of the biased noise-floor power estimate.

1 8. The method of claim 2, wherein:
2 Z is the biased noise-floor power estimate;
3 τ_k is a time delay;
4 γ is the noise-scaling factor;
5 h_k is a plurality of power values;
6 N_p is a plurality of the plurality of power values h_k ; and

7 the center-of-gravity position estimate is $\frac{\sum_{k=1}^{N_p} \tau_k (h_k - \gamma Z)}{\sum_{k=1}^{N_p} (h_k - \gamma Z)}$.

1 9. The method of claim 1, wherein:
2 Z is the biased noise-floor power estimate;
3 γ is the noise-scaling factor;
4 h_k is a plurality of power values; and
5 the noise-corrected power delay profile is $h_k - \gamma Z$.

1 10. The method of claim 1, wherein:
2 σ_g^2 is the biased noise-floor power estimate;
3 Z^* is a mean power of a plurality of values h_k ;
4 γ is the noise-scaling factor; and
5 $\gamma = \frac{Z^*}{\sigma_g^2}$.

11. The method of claim 1, wherein:

γ' is the noise-scaling factor;

$$\gamma' = \frac{N_{paths} + \gamma(N_p - N_{paths})}{N_p};$$

N_p is a plurality of power values;

N_{paths} is a number of true paths among the N_p power values

σ_g^2 is the biased noise-floor power estimate;

Z^* is a mean power of a plurality of power values N_n ; and

$$\gamma = \frac{Z^*}{\sigma_g^2}.$$

12. The method of claim 2, further comprising:

determining the noise-scaling factor;

storing the noise-scaling factor for on-line use; and

wherein the step of determining the noise-scaling factor is performed offline and

before the steps of determining the power delay profile, calculating the noise-corrected power delay profile, and calculating the center-of-gravity position estimate.

1 13. An apparatus for determining a noise-corrected power delay profile, the
2 apparatus comprising:
3 a channel estimator;
4 a despreader; and
5 a delay estimator interoperably connected to the channel estimator and the despreader,
6 the delay estimator for:
7 determining a power delay profile;
8 calculating a noise-corrected power delay profile; and
9 wherein the step of calculating the noise-corrected power delay profile
10 comprises using a biased noise-floor power estimate, the power delay profile, and a
11 noise-scaling factor.

1 14. The apparatus of claim 13, wherein the delay estimator is further for:
2 calculating a center-of-gravity position estimate; and
3 wherein the step of calculating the center-of-gravity position estimate
4 comprises using the noise-corrected power delay profile.

1 15. The apparatus of claim 13, wherein the noise-scaling factor is applied to the
2 biased noise-floor power estimate.

1 16. The apparatus of claim 13, wherein the noise-scaling factor is dependent upon
2 a probability density function.

1 17. The apparatus of claim 13, wherein:
2 the step of determining the power delay profile comprises using a first plurality of
3 values; and
4 the step of calculating the noise-corrected power delay profile comprises using the
5 first plurality of values and a second plurality of values.

1 18. The apparatus of claim 17, wherein:
2 the first plurality of values is a plurality of power-delay-profile values N_p ; and
3 the second plurality of values is the N_n smallest power-delay-profile values.

1 19. The apparatus of claim 18, wherein the noise-scaling factor is dependent upon
2 a probability density function of the biased noise-floor power estimate.

1 20. The apparatus of claim 14, wherein:
2 Z is the biased noise-floor power estimate;
3 τ_k is a time delay;
4 γ is the noise-scaling factor;
5 h_k is a plurality of power values;
6 N_p is a plurality of the plurality of power values h_k ; and
7 the center-of-gravity position estimate is $\frac{\sum_{k=1}^{N_p} \tau_k (h_k - \gamma Z)}{\sum_{k=1}^{N_p} (h_k - \gamma Z)}$.

1 21. The apparatus of claim 13, wherein:
2 Z is the biased noise-floor power estimate;
3 γ is the noise-scaling factor;
4 h_k is a plurality of power values; and
5 the noise-corrected power delay profile is $h_k - \gamma Z$.

1 22. The apparatus of claim 13, wherein:
2 σ_g^2 is the biased noise-floor power estimate;
3 Z^* is a mean power of a plurality of values h_k ;
4 γ is the noise-scaling factor; and
5 $\gamma = \frac{Z^*}{\sigma_g^2}$.

1 23. The apparatus of claim 13, wherein:

2 γ' is the noise-scaling factor;

3
$$\gamma' = \frac{N_{paths} + \gamma(N_p - N_{paths})}{N_p};$$

4 N_p is a plurality of power values;

5 N_{paths} is a number of true paths among the N_p power values

6 σ_g^2 is the biased noise-floor power estimate;

7 Z^* is a mean power of a plurality of power values N_n ; and

8
$$\gamma = \frac{Z^*}{\sigma_g^2}.$$

1 24. The apparatus of claim 14, further comprising:

2 determining the noise-scaling factor;

3 storing the noise-scaling factor for on-line use; and

4 wherein the step of determining the noise-scaling factor is performed offline and

5 before the steps of determining the power delay profile, calculating the noise-corrected power

6 delay profile, and calculating the center-of-gravity position estimate.

1 25. An article of manufacture for determining a noise-corrected power delay
2 profile, the article of manufacture comprising:
3 at least one computer readable medium; and
4 processor instructions contained on the at least one computer readable medium, the
5 processor instructions configured to be readable from the at least one computer readable
6 medium by at least one processor and thereby cause the at least one processor to operate as
7 to:
8 determine a power delay profile;
9 calculate a noise-corrected power delay profile; and
10 wherein the calculation of the noise-corrected power delay profile
11 comprises using a biased noise-floor power estimate, the power delay profile, and a
12 noise-scaling factor.

1 26. The article of manufacture of claim 25, wherein the processor instructions are
2 further configured to cause the at least one processor to operate as to:
3 calculate a center-of-gravity position estimate; and
4 wherein the calculation of the center-of-gravity position estimate comprises
5 using the noise-corrected power delay profile.